


Autonomous dispenser / reloader of magnetic cards for vending machines



According to the Cartadis DRC9STD Vending chosen, magnetic reloadable Cartadis cards can be sold and reloaded against coin and/or banknote insertion (description overleaf).

It enables cards to be dispensed automatically to users who had none, or reloaded, whether their credit had already been spent out or not.

With **Cartadis DRC9STD Vending** and a set of Cartadis terminals, you can fit out a site **for full "self-service" operation.**

The DRC9 advantages

- ✓ A full "self-service" operation of the service.
- ✓ An intuitive and ergonomic touchscreen that allows the display of the user credit and prices.
- ✓ Buying or reloading of cards by using coins and/or banknotes.
- ✓ Buying or reloading of cards with 6 decreasing prices available.
- ✓ Buying and dispensing of reloadable Cartadis user cards.
- ✓ For a site management without requiring staff for selling cards.

Statistics

Reloading statistics can be read by the person in charge of the unit and viewed on the screen, or downloaded via an USB key. These data consist of: receipt on the current period, receipt from installation and number of cards sold.

Card buying or reloading a card

✓ The user can buy or reload a card as follows:



- | | |
|--|---|
| <ul style="list-style-type: none"> ✓ Buying a card is composed of 4 steps: <ul style="list-style-type: none"> ○ Selecting of the service wished (buying or reloading) on the touchscreen, ○ Inserting money with simultaneous display of credit, ○ Recovering of the card dispensed in the DRC9STD Vending receiver, ○ Inserting the card in the reader for credit loading. | <ul style="list-style-type: none"> ✓ Reloading a card is composed of 3 steps: <ul style="list-style-type: none"> ○ Selecting of the service wished (buying or reloading) on the touchscreen, ○ Inserting money with simultaneous display of credit, ○ Inserting the card in the reader for credit loading. |
|--|---|

The range of DRC9 Vending dispensers / reloaders

The range of DRC9 Vending dispensers / reloaders enables the various ways of payment to be accepted.

	DRC9STD Vending - P	DRC9STD Vending - P - B	DRC9STD Vending - B
Coin mechanism (6 different coins)	X	X	
Banknote reader (3 different banknotes)		X	X

Specifications

- ✓ Card feeder capacity: about 350 cards.
- ✓ Automatic withhold of the card dispensing when the feeder is empty, but reloading maintained.
- ✓ 7 inch touchscreen, resolution 800*480, 16 million colours.
- ✓ Housing in 2 mm thick plate, closed by a 3 point-lock.
- ✓ Option: banknote stacker (capacity: 300 banknotes).
- ✓ Power supply: 230 Volts - 25 Watts.
- ✓ Dimensions: height 91 cm - width 48 cm, depth 50 cm (base).
- ✓ Empty weight about 33 kg.

CARTADIS

Zone des Marais – 1 Av., Louison Bobet
94120 Fontenay-sous-Bois – France
Phone: (33) 01 48 77 40 60 - Fax: (33) 01 48 77 36 47
E-mail: sales@cartadis.com
Web: www.cartadis.com

Your local dealer